



PRECISION STOPPING STARTS **HERE!**

EURO HÜBNER
BENELUX B.V.

**Technical
Data**

**FWM-03
FWM-05**

HWM-05

VM-05

Input Voltage

460Vac/50-60Hz

400V/50-60Hz

Coil Voltage

Max. 400Vdc

Max. 220Vdc

Max. 400Vdc

Max. constant
Energy Absorption

3W

5W

5W

Suitable for
brake type

KFB5...KFB40
SFB10...SFB40

KFB40...KFB160
SFB40...SFB1000

KFB5...KFB160
SFB10...SFB1000

Max Coil
Current

FWM-03: 2,5A
FWM-05: 5A

5A

5A

Rectifier FWM:

Full Wave rectifiers for Din-rail mounting.

Rectifier HWM:

Half Wave rectifiers for Din-rail mounting.

Protective Element VM:

Designed to be connected parallel to the output of the rectifiers, thereby increasing the interruption capacity.

Features

- ☒ Integrated protective element
- ☒ Combinable with BMM (Brake Monitoring Module)
- ☒ EMC compatibility

☒ High Quality Products

☒ Large stock in our Local Warehouse

☒ Easy Installation

☒ High Safety Standards

T +31 (0)475 406 506

I www.euro-hubner.nl

E sales@euro-hubner.nl

EURO HÜBNER
BENELUX B.V.

SMART
INCONTROL

EL EUROPE
LIGHTING

TransMoTech
group